Mechanical force gauge SAUTER FA





Mechanical force gauge for tensile and compressive force measurements with peak hold function

Features

- Dual scale: shows Newton and kg
- Turnable display unit for an easy zero setting of the instrument
- Peak hold function by drag pointer
- Can be mounted on all manual test stands
- Zeroing by a short push of the switch
- 1 Delivered in a robust carrying case
- 2 Standard attachments as shown, extension rod: 90 mm

Technical data

- Measuring precision: 1 % of [Max]
- Overall dimensions W×D×H 232×60×51 mm
- Thread: M6
- Net weight approx. 0,55 kg

Accessories

- 2 Standard attachments as standard, set can be reordered, SAUTER AC 43
- Further accessories see page 40 onwards or our website

STANDARD: PEAK, PUSH/PULL, ZERO, 1 DAY
OPTION: ISO +4 DAYS

Model	Measuring range	Readout	Option **Factory calibration certificate**		
			Tensile force	**Compressive force**	**Tensile/Compressive force**
SAUTER	[Max] N	[d] N	KERN	KERN	KERN
FA 10	10	0,05	961-161O	961-261O	961-361O
FA 20	20	0,1	961-161O	961-261O	961-361O
FA 50	50	0,25	961-161O	961-261O	961-361O
FA 100	100	0,5	961-161O	961-261O	961-361O
FA 200	200	1	961-161O	961-261O	961-361O
FA 300	300	2	961-161O	961-261O	961-361O
FA 500	500	2,5	961-161O	961-261O	961-361O

Further calibration options on request

SAUTER GmbH · c/o KERN & SOHN GmbH · Ziegelei 1 · 72336 Balingen · Germany · Tel. +49 7433 9933-0 · www.kern-sohn.com · info@kern-sohn.com

Adjusting program (CAL):
For quick setting of the instrument's accuracy. External adjusting weight required

Calibration block:
Standard for adjusting or correcting the measuring device

Peak hold function:
Capturing a peak value within a measuring process

Scan mode:
Continuous capture and display of measurements

Push and Pull:
The measuring device can capture tension and compression forces

Length measurement:
Captures the geometric dimensions of a test object or the movement during a test process

Focus function:
Increases the measuring accuracy of a device within a defined measuring range

Internal memory:
To save measurements in the device memory

Data interface RS-232:
Bidirectional, for connection of printer and PC

Profibus:
For transmitting data, e.g. between scales, measuring cells, controllers and peripheral devices over long distances. Suitable for safe, fast, fault-tolerant data transmission. Less susceptible to magnetic interference.

Profinet:
Enables efficient data exchange between decentralised peripheral devices (balances, measuring cells, measuring instruments etc.) and a control unit (controller). Especially advantageous when exchanging complex measured values, device, diagnostic and process information. Savings potential through shorter commissioning times and device integration possible

Data interface USB:
To connect the measuring instrument to a printer, PC or other peripheral devices

Bluetooth* data interface:
To transfer data from the balance/measuring instrument to a printer, PC or other peripherals

WLAN data interface:
To transfer data from the balance/measuring instrument to a printer, PC or other peripherals

Data interface Infrared:
To transfer data from the measuring instrument to a printer, PC or other peripheral devices

Control outputs (optocoupler, digital I/O):
To connect relays, signal lamps, valves, etc.

Analogue interface:
To connect a suitable peripheral device for analogue processing of the measurements

Analog output:
For output of an electrical signal depending on the load (e.g. voltage 0 V – 10 V or current 4 mA – 20 mA)

Statistics:
Using the saved values, the device calculates statistical data, such as average value, standard deviation etc.

PC Software:
To transfer the measurement data from the device to a PC

Printer:
A printer can be connected to the device to print out the measurement data

Network interface:
For connecting the scale/measuring instrument to an Ethernet network

KERN Communication Protocol (KCP):
It is a standardized interface command set for KERN balances and other instruments, which allows retrieving and controlling all relevant parameters and functions of the device. KERN devices featuring KCP are thus easily integrated with computers, industrial controllers and other digital systems

GLP/ISO record keeping:
Of measurement data with date, time and serial number.
Only with SAUTER printers

Measuring units:
Weighing units can be switched to e.g. non-metric. Please refer to website for more details

Measuring with tolerance range (limit-setting function):
Upper and lower limiting can be programmed individually. The process is supported by an audible or visual signal, see the relevant model

Protection against dust and water splashes IPxx:
The type of protection is shown in the pictogram cf. DIN EN 60529:2000-09, IEC 60529:1989+A1:1999+A2:2013

ZERO:
Resets the display to "0"

Battery operation:
Ready for battery operation. The battery type is specified for each device

Rechargeable battery pack:
Rechargeable set

Plug-in power supply:
230V/50Hz in standard version for EU. On request GB, AUS or USA version available

Integrated power supply unit:
Integrated, 230V/50Hz in EU. More standards e.g. GB, AUS or USA on request

Motorised drive:
The mechanical movement is carried out by a electric motor

Motorised drive:
The mechanical movement is carried out by a synchronous motor (stepper)

Fast-Move:
The total length of travel can be covered by a single lever movement

Verification possible:
Models with type approval for construction of verifiable systems

DAkkS calibration possible:
The time required for DAkkS calibration is shown in days in the pictogram

Factory calibration:
The time required for factory calibration is specified in the pictogram

Package shipment:
The time required for internal shipping preparations is shown in days in the pictogram

Pallet shipment:
The time required for internal shipping preparations is shown in days in the pictogram

*The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by KERN & SOHN GmbH is under license. Othear trademarks and trade names are those of their respective owners.